

# Bardac drives

## K-Series single phase DC drives

**Up to 2 horsepower**

**4-Quadrant Reversing Regenerative & Non-regenerative  
Isolated & Non-isolated Control**

Enclosed, DIN rail mounting drives in elegant compact packages for both stand alone and systems applications. Features include plug-in screw terminals, dual 115 & 230 volts, 50/60Hz supply, armature volts or tach feedback and optional interface to the **drive.web** Internet accessible distributed control technology.



**Model K340**



**Model K680**



**Model K1220XRi**

MODEL	RATING	SIZE	FEATURES	TERMINALS		
<b>NON-ISOLATED</b>						
K340	1/4Hp 0.25kW @90Vdc 1/2Hp 0.55kW @180Vdc Field 1Amp 0.9x ac supply	1.4" W 4.2" H 4.7" D	Max Speed Min Speed Up Ramp IR Comp	+10V Min Input + Common	A+ A- F+ F-	
K680	1/2Hp 0.55kW @90Vdc 1Hp 0.75kW @180Vdc Field 1Amp 0.9x ac supply	1.8" W 4.2" H 4.7" D	I max AVF/Tach switch Speed range switch	Run Tach f/b	L N	
K1220	1Hp 0.75kW @90Vdc 2Hp 1.8kW @180Vdc Field 1Amp 0.9x ac supply	1.8" W 4.2" H 4.7" D	AC voltage selector			
<b>ISOLATED</b>						
K340i	1/4Hp 0.25kW @90Vdc 1/2Hp 0.55kW @180Vdc Field 1Amp 0.9x ac supply	2.4" W 4.2" H 4.7" D	Max Speed Min Speed Up Ramp Down Ramp	+10V ref Min speed Input + Output +/-	Level O/P Level i/P Overload Trip	A+ A- F+ F-
K680i	1/2Hp 0.55kW @90Vdc 1Hp 0.75kW @180Vdc Field 1Amp 0.9x ac supply	2.8" W 4.2" H 4.7" D	Stability I max IR Comp	Common Input +/- Pushbutton +	Ramp O/P Demand O/P Speed O/P	L N
K1220i	1Hp 0.75kW @90Vdc 2Hp 1.8kW @180Vdc Field 1Amp 0.9x ac supply	2.8" W 4.2" H 4.7" D	Speed range switch AC voltage selector Level comparator	Pushbutton - Run Common Tach f/b	Current O/P + Speed I/P Torque I/P	
<b>4-QUADRANT, REGENERATIVE, REVERSING, ISOLATED</b>						
K340XRi	1/4Hp 0.25kW @90Vdc 1/2Hp 0.55kW @180Vdc Field 1Amp 0.9x ac supply	2.4" W 4.2" H 4.7" D	Max Speed Min Speed Up Ramp Down Ramp	+10V ref Min speed Input + Output +/-	Level O/P Level i/P Overload Trip	A+ A- F+ F-
K680XRi	1/2Hp 0.55kW @90Vdc 1Hp 0.75kW @180Vdc Field 1Amp 0.9x ac supply	2.8" W 4.2" H 4.7" D	Stability I max IR Comp	Common Input +/- Pushbutton +	Ramp O/P Demand O/P Speed O/P	L N
K1220XRi	1Hp 0.75kW @90Vdc 2Hp 1.8kW @180Vdc Field 1Amp 0.9x ac supply	2.8" W 4.2" H 4.7" D	Speed range switch AC voltage selector Level comparator	Pushbutton - Run Common Tach f/b	Current O/P + Speed I/P Torque I/P	

Bardac Corporation 40 Log Canoe Circle, Stevensville, MD 21666 USA

Phone toll free USA 888-667-7333 or 410-604-3400, Fax 410-604-3500, [www.bardac.com](http://www.bardac.com), [www.driveweb.com](http://www.driveweb.com)