

# Bardac DC Drive Datasheet

Model: 3200i/32C109

**3200i/32C109 | 32A, 1-ph, 230V/460V, Non-Regen, Non-Reversing, Fully Isolated DC Drive**

## Input Ratings

Supply Voltage	230V, 1-ph in   460V, 1-ph in
Input Current	48 Amps

## Output Ratings

Power at 180VDC	5 HP
Power at 360VDC	8 HP
Max Field Current	2 Amps
Max Armature Current	32 Amps
Regen	No

## Factory Build Options

Enclosure	Open Chassis
Frame Size	0
Dimensions (W x H x D)	7.87" x 5.9" x 4.33"

## Miscellaneous

Feedback Types	Armature, Tachometer
Max Watts Loss	96 Watts

