

Bardac DC Drive Datasheet

Model: 3200i/32

3200i/32 | 32A, 1-ph, 120V/230V, Non-Regen, Non-Reversing, Fully Isolated DC Drive

Input Ratings

Supply Voltage	120V, 1-ph in 230V, 1-ph in
Input Current	48 Amps

Output Ratings

Power at 90VDC	3 HP
Power at 180VDC	6 HP
Max Field Current	2 Amps
Max Armature Current	32 Amps
Regen	No

Factory Build Options

Enclosure	Open Chassis
Frame Size	0
Dimensions (W x H x D)	7.87" x 5.9" x 4.33"
Weight	LBS

Miscellaneous

Feedback Types	Armature, Tachometer
Max Watts Loss	96 Watts

