

# Bardac DC Drive Datasheet

Model: 3600XRi/32

**3600XRi/32 | 32A, 1-ph, 120V/230V, Regen, Reversing, Fully Isolated DC Drive**

## Input Ratings

Supply Voltage	120V, 1-ph in   230V, 1-ph in
Input Current	48 Amps

## Output Ratings

Power at 90VDC	3 HP
Power at 180VDC	6 HP
Max Field Current	2 Amps
Max Armature Current	32 Amps
Regen	Yes

## Factory Build Options

Enclosure	Open Chassis
Frame Size	0
Dimensions (W x H x D)	7.87" x 6.89" x 2.76"
Weight	LBS

## Miscellaneous

Feedback Types	Armature, Tachometer
Max Watts Loss	96 Watts

