

# Bardac DC Drive Datasheet

Model: 3600XRi/32C132

3600XRi/32C132 | 32A, 1-ph, 230V/460V, Regen, Reversing, Fully Isolated DC Drive

## Input Ratings

Supply Voltage	230V, 1-ph in   460V, 1-ph in
Input Current	48 Amps

## Output Ratings

Power at 180VDC	6 HP
Power at 320VDC	10 HP
Max Field Current	2 Amps
Max Armature Current	32 Amps
Regen	Yes

## Factory Build Options

Enclosure	Open Chassis
Frame Size	0
Dimensions (W x H x D)	7.87" x 6.89" x 2.76"

## Miscellaneous

Feedback Types	Armature, Tachometer
Max Watts Loss	96 Watts

