

# Bardac DC Drive Datasheet

Model: 400i

**400i | 4A, 120V/230V, Non-Regen, Non-Reversing, Fully Isolated DC Drive**

## Input Ratings

Supply Voltage	120V, 1-ph in   230V, 1-ph in
Input Current	6 Amps

## Output Ratings

Power at 90VDC	0.4 HP
Power at 180VDC	0.75 HP
Max Field Current	0.5 Amps
Max Armature Current	4 Amps
Regen	No

## Factory Build Options

Enclosure	Open Chassis
Frame Size	0
Dimensions (W x H x D)	3.93" x 6.3" x 1.97"
Weight	2 LBS

## Miscellaneous

Feedback Types	Armature, Tachometer
Max Watts Loss	12 Watts

